

## FUEL INJECTOR CCLEANER TESTER IC 6A 1



Power supply	: AC220V±10%/50Hz~60Hz
Input power	: 250W
Ultrasonic cleaning power	: 100W
Simulated RPM range	: 10~9990rpm; step: 10rpm
Count range	: 1~9999 times
Pulse width	: 0.5~25ms; step 0.1 ms
Fuel tank capacity	: 4700ml
Dimensions	: 550mm × 530mm × 1400 mm
Weight	: About 80kg.